

Handheld Remote Controller LLP-LO-REMCC



ON	OFF	ON Turn On	OFF Turn Off
		Matching code for light Keep the "ID" button pressed in to keep the controller's indicator on, then turn on the light and release the "ID" button after the light starts flashing, the matching code is then complete. Matching code for several lights simultaneously is also available.	
		Release the code and disconnect light from remote controller Press the bottom "ID" + together, then turn on the light, the light will flash when it is disconnected from the controller	
		Group selection button Grouping lights (matching code process needs to be completed first). Turn off the lights, press the group selection button for 3s, then turn on the lights, the lights will flash to finish grouping.	
		Turn off delay Press the button, the delay function will begin after the light flashed once. The light will be turned off after 10s. Pressing the "ON" button will cancel the delay function	
		All groups are selected	
Color temperature selecting/saving After selecting the color temperature, press the button "OFF" then turn on the light to save the color temperature.			
5000K 4000K		3500K 3000K	
25% brightness 50% brightness		75% brightness 100% brightness	
increase brightness decrease brightness		decrease color temperature increase color temperature	

* After turned on, the light will automatically detect the 0-10v dimming setting to determine the brightness. It will default to 100% brightness if there is no dimmer input.

* If the dimmer is used, the light brightness will convert to 0-10v dimmer's current brightness setting.

* If the remote controller is used, the light brightness will only change from its current brightness.